Examination: November-December 2017 **Date:** 22-11-17 **Branch:** Computer Engineering **Subject:** DSP

Class/SEM: BE/VII Paper Code: 22974

Examination: November-December 2017 **Date:** 28-11-17 **Branch:** Computer Engineering **Subject:** CSS

Class/SEM: BE/VII Paper Code: 24641

Examination: November-December 2017 **Date:** 5/12/2017

Branch: Computer Engineering Subject: Al

Class/SEM: BE/VII Paper Code: 24610

Examination: November-December 2017 **Date:** 12/12/2017

Branch: Computer Engineering **Subject:** SC

Class/SEM: BE/VII Paper Code: 22936

Examination: November-December 2017 **Date:** 12/12/2017

Branch: Computer Engineering Subject: SA

Class/SEM: BE/VII Paper Code: 27659

B.E / Compl Sem VII (CBS48/ DSP/ 22411/17

QP CODE: 22974

+		(3 hours) Total Marks: 80	
N.B.	3	Question No. 1 is compulsory Attempt any three out of remaining Assume suitable data if necessary and justify the assumptions Figures to the right indicate full marks	
Q1	A	Compare microprocessor with digital signal processor.	05
	В	State whether $x[n] = \cos(3\pi n/4)$ is an energy or power signal with proper justification.	05
	С	Find the cross correlation of two causal sequences $x[n] = \{2, 3, 1, 4\}$ and $y[n] = 3 \delta(n-3) - 2 \delta(n) + \delta(n-1) + 4 \delta(n-2)$.	05
	D	State BIBO stability criterion for LTI systems. Test the stability of the LTI	05
Q2	A	systems, whose impulse response is: h[n] = 0.2 ⁿ u[-n] +3 ⁿ u[-n]. Check whether the system y[n]= a ⁿ u[n] is: i)Static or Dynamic ii)Linear or Non-linear iii)Causal or Non-Casual iv) Shift variant or Shift Invariant	10
	В	Consider analog signal $x(t) = 2 \sin 80\pi t$. If the sampling frequency is 60 Hz, find the sampled version of discrete time signal $x[n]$ also find an alias frequency corresponding to Fs = 60 Hz.	10
Q3		Determine the output response of the LTI system using tabular method, whose input is: $x[n]=1$; $n=0, 1$ $= 3$; $n=2, 3$ $= 0$; elsewhere	LIERAR
		and $h[n] = \delta[n] - 2\delta[n-1] + 3\delta[n-2] - 4\delta[n-3]$. Compute DFT of sequence $x[n] = \{0, 2, 3, -1\}$. Sketch the magnitude and	10
		phase spectrum.	10
14	4	Explain the following properties of DFT: i)Periodicity ii)Linearity iii)Time Shift iv)Circular Convolution	10
I	3	v)Time Reversal Compute linear convolution of the causal sequences $x[n] = \{4, 4, 3, 3, 2, 2, 1, 1\}$ and $h[n] = \{-1, 1\}$ using overlap save method.	10

[TURN OVER]

EGOISMAADE2DO3BORDSIDEDE1D0771E

Q5	A	In a LTI system the input $x[n] = \{1, 2, 1\}$ and impulse response is $h[n] = \{1, 3\}$. Determine the response of LTI system using radix- 2 DIT FFT method.	10
	В	Explain Parseval's energy theorem.	10
		If IDFT $\{X(k)\}=x[n]=\{2,1,2,0\}$ using DFT properties, evaluate the	
		following:	
		i)IDFT of {X(k-1)}	
		ii)IDFT of {X(k) circularly convolved with X(k)} iii)IDFT of {X(k).X(k)} iv)Signal energy	
Q6	A	Explain the significance of Carl's Correlation Coefficient Algorithm in digital signal processing. Evaluate Carl's Coefficient for two causal sequences $x[n]=\{3, 4, 7, 8\}$ and $y[n]=\{2, 1, 1, 2\}$.	10
	В	complex additions and multiplications required	5
		ii) Write a detailed note on biomedical applications of DSP processors.	5

B.E/ Comp/ Sem VIII CBS45/ C+ SS/ 28/11/17

Q. P. Code: 24641

	(Time: 3hrs) (Marks 80)	
	Question No 1 is compulsory. Attempt any three out of the remaining five questions.	
QI	key = 15. Decrypt to get back original plaintent	05
	ciphers and polyalphabetic ciphers?	05
	(c) What are the properties of hash functions? What is the role of a hash function in security?	05
	(d) What are the different protocols in SSL? How do the client and server establish an SSL connection	05
Q2	(a) What is a digital certificate? How does it help to validate the authenticity of a user? Explain the X.509 certificate format.	10
	 (b) With reference to DES comment on the following: i) Block size and key size ii) Need for expansion permutation iii) Avalanche and completeness effects iv) Weak keys and semi-weak keys v) Role of S-box. 	10
Q3.	(a) What are the different types of viruses and worms? How do they propagate?(b) What are the various ways for memory and address protection in Operating System?	10 10
Q4.	(a) Explain briefly with examples, how the following attacks occur: i) Phishing attack ii) Denial of Service attack iii) SQL injection attack iv) Cross-site scripting attack (b) How is security achieved in the transport and the security achieved in the security achieve	10
	(b) How is security achieved in the transport and tunnel modes of IPSec? What are security associations?	10
Q5.	(a) What are the different threats to emails? Give an algorithm to secure emails being sent from user A to user B.	10
1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	(b) A and B wish to use RSA to communicate securely. A chooses public key as (7,119) and B chooses public key as (13,221). Calculate their private keys. A wishes to send message m=10 to B. What will be the ciphertext? With what key will A encrypt the message "m" if A needs to authenticate itself to B.	10

Page 1 of 2

Q. P. Code: 24641

	C. 2. Code: 24641	
Q6.	i) Block and stream ciphers ii) MD-5 versus SHA	10
	 iii) Key generation in IDEA and Blowfish (b) What are the different components of an Intrusion Detection System? Compare the working of signature based IDS with anomaly based IDS. 	10

omp /sem VII / CBSGS/AI/05/12/17

3 Hours

Q. P. Code: 24610

Total Marks = 80

Note:

- (i) Each question carries 20 marks
- (ii) Question 1 is compulsory
- (iii) Attempt any three (3) from the remaining questions
- (iv) Assume suitable data wherever required

Q1. Attempt any four (4) questions from the following:

- (a) Give PEAS description for an Autonomous Mars Rover. Characterize its environment.
- (b) Give the initial state, goal test, successor function, and cost function for the following

"You have to colour a planar map using only 4 colours, in such a way that no two adjacent regions have the same colour".

- (c) Draw and explain architecture of Expert System.
- (d) Explain Hill-climbing algorithm with an example.
- (e) Covert the following propositional logic statement into CNF
 - $A \rightarrow (B \leftarrow \rightarrow C)$




Q2. (a). Explain decision tree learning with an example.

[10]


[10]

- (b) Write first order logic statements for following statements:
 - Horses, cows, and pigs are mammals.
 - (ii) Bluebird is a horse.
 - (iii) Whoever can read is literate.
 - Every tree in which any aquatic bird sleeps is beside some lake. (iv)
 - Anything anyone eats and is not killed by is food. (v)
- Q3. (a) Design a planning agent for a Blocks World problem. Assume suitable initial state and final state for the problem. [10]
 - (b) Consider a situation in which we want to reason about the relationship between smoking and lung cancer. Intuitively, we know that whether or not a person has cancer is directly influenced by whether she is exposed to second-hand smoke and whether she smokes. Both of these things are affected by whether her parents smoke. Cancer reduces a person's life expectancy.
 - (i) Draw the Bayesian network.
 - (ii) How many independent values are required to specify all the conditional probability tables (CPTs) for your network?
- Q4. (a) Compare Greedy Best first search and A* search algorithms based on performance measure with justification: Complete, Optimal, Time and Space complexity.
 - (b) Write a pseudocode for alpha-beta algorithm. Apply alpha-beta pruning on example given in Figure 1 considering first node as max. [4+6]

Q. P. Code: 24610



- Q5. (a) Define the terms chromosome, fitness function, crossover and mutation as used in Genetic algorithms. Explain how Genetic algorithms work? [4+6]
 - (b) Consider the graph given in Figure 2 below. Assume that the initial state is A and the goal state is G. Show how Greedy Best first Search would create a search tree to find a path from [10]



At each step of the search algorithm, show which node is being expanded, and the content of fringe. Also report the eventual solution found by the algorithm, and the solution cost. Assuming the straight-line distance as the heuristics function: h(S)=10.5, h(A)=10, h(B)=6, h(C)=4, h(D)=8, h(E)=6.5, h(F)=3 and h(G)=0.

Q6. Answer any two (2) of the following

(i) What are steps involved in natural language processing (NLP) of an English sentence? Explain with an example sentence.

(ii) Draw and explain the basic building blocks of Learning Agent.

(iii) How will you convert the propositional logic statement into CNF? Give a suitable example at each step.

B. E | Sem VII | Comp | CBS GS | Sc / 12/12/13

Q.P. Code: 22936

(3 Hours)

Total Marks: 80

N.B : (1) Question No. 1 is compulsory

(2) Attempt any three questions out of remaining five.

- Distinguish between hard computing and soft computing. 1. (a) 5 Explain fuzzy extension principle with suitable example. (b) 5 5 Prove that $f'(net) = (1 - O^2)/2$ for bipolar continuous activation function 5 What are hybrid systems? Explain any 2 types of hybrid systems. 10 Explain EBPTA with the help of block diagram. 2. What do you understand by learning? Compare the different learning rules w.r.t 10 weight adjustments, initial weights, type of learning, neuron characteristics and number of neurons. Design a fuzzy logic controller for an air-conditioner. Consider room temperature 20 3. and humidity as input and AC temperature as output. Use four descriptors each for inputs and output. Derive proper set of rules and using appropriate defuzzification technique get exact AC temperature. The design should be supported by appropriate figures. Also prove that if the room temperature is hot and humidity is high then the AC temperature is set to cool.
- 4. (a) Explain working of LVQ with the help of an algorithm. Also construct and test an LVQ net with five vectors assigned to two classes. The given vectors along with the classes are as shown in Table 1.

Vector	Class
[0.04.1]	1
[1000]	2
[0 0 0 1]	2
[1 1 0 0]	1
[0 1 1 0]	1

10

10



Consider $\alpha = 0.1$. Show the weight change for only one epoch.

(b) Draw and explain the architecture of ANFIS. Briefly explain the application of ANFIS.

Q.P. Code: 22936

- 5. Explain Genetic Algorithm with a suitable flowchart. Explain Roulette wheel selection and rank selection methods used in GA. 10
 - Explain the alpha cut and strong alpha cut features of fuzzy membership 10

Also consider the following fuzzy sets.

B = {
$$(1, 1), (0.9, 2), (0.8, 3), (0.3, 4), (0.4, 5), (0.5, 6), (0.6, 7)$$
}
Find the following

$$(A \cap \overline{B})_{0.4}$$

- (a) What is linear separability? Using the linear separability concept, obtain the 6. response for AND function with bipolar inputs and targets. 10
 - (b) Explain the Newton's methods of derivative based optimization techniques. 10

E/Sem VIII / Comp/ CASGS/SA/ 12/12/17

Q.P. Code: 27659

1	Q.P. Code: 27659		
1	[Time: 3 Hours]	farks: 80]	
	Please check whether you have got the right question paper. N.B: 1. Question No. 1 is compulsory. 2. Attempt any three questions out of remaining questions. 3. Make suitable assumptions whenever necessary.		
Q.1. a)	Design Domain-Specific Software Architecture (DSSA) for online Admission in First Year Engineering Colleges website Management System. Assume suitable entities, attributes e Domain Model must consists following: a) Domain Dictionary and Information Model. b) Feature Model and Operational Model.	20 tc.	
	Define Architectural patterns. Explain any one Pattern with an example.	10	
2.2. a) b)		10	
.3. a) b)	"Focus on Architecture is focus on Reuse". Comment. What is perspective and descriptive architecture? Give one Example.	10 10	
,	Explain the distributed object style in connection with CORBA middleware. Discuss Design issues for NFP's: Complexity and Heterogeneity.	10 10	
	Discuss frameworks for the Pipe-and-Filter Architectural Style. What is REST? Explain its Architecture.	10 10	
6. a) (Write short notes on the following. (Any Two) a) xADL; b) ATAM; c) Stakeholder driven modelling d) SOA and Web Services.	LIST LIST	